

Datasheet

V5-024 18V - 2.2A DC Power Supply for V5/V9 IRS installations

- 18V DC 2.2A power supply adequate for up to 25 multiswitches, and an LNB
- Ideal for remote line powered systems where mains is not near headend
- Ideal for remote powering of V5 systems via DC inserter or direct to multiswitch
- Switch-mode design for cool running and reliable performance
- F connector for reliable DC connection to system
- Built-in fixing lugs
- UK plug with 3.0A fuse fitted
- LED Power Indicator



V5 and V9 IRS can be powered using the V5-024 via the H,Lo and H,Hi trunk cables or by DC connection into the auxiliary DC socket of a multiswitch. This flexibility means that power can be inserted at almost any point in the system even where there is no main power near the headend amplifiers.

See also V5-023 DC Line Power Injector

Model	V5-024
Output Voltage	18V DC
Output Current	2.2A 39.6VA
Mains Voltage	180 - 264V AC 50Hz
Mains Current	300mA 39.6VA
Connector	600mm DC lead with F Connector
Mains Lead	600mm mains lead with UK mains plug with 3.0A fuse
IP Rating	Indoor Use Only. Do not mount near sources of moisture, humidity or high temperature
Ambient Temperature	-20 to +50°C
Size inc fixing lugs (mm)	140 x 65 x 57
Weight	0.3kg

In the interests of continued product development & improvement, Vision Products (Europe) Ltd reserves the right to change product specifications, design & dimensions. Data correct at time of going to press.